

## Lectrosonics Wireless Switch Settings/Frequency Charts

### Frequency Adjustment Switches

To gain access to these switches, slide the access door open with a fingernail. These two rotary switches change the frequency of the unit. The frequency range (block) of the unit is laser engraved on this switch cover or the housing.



### Adjusting the Frequency

If you are experiencing interference from another signal on your frequency, you may want to change the operating frequency of your system. The left switch changes the operating frequency in large steps and the right switch changes it in fine steps. If you are experiencing interference, change the operating frequency in fine steps to find a clear channel. If it is not possible to find a clear channel using the fine switch, return it to its original position and change the left switch by one click then try the right switch again. Important - make certain that the switches on the transmitter and receiver are set to the same position. If not, the system will not be on matched frequencies and will not work. Transmitter and receiver must also be on the same block.

[Block 20](#) 512.000 to 537.500 MHz

[Block 21](#) 537.600 to 563.100 MHz

[Block 22](#) 563.200 to 588.700 MHz

[Block 23](#) 588.800 to 614.300 MHz

[Block 24](#) 614.400 to 639.900 MHz

[Block 25](#) 640.000 to 665.500 MHz

[Block 26](#) 665.600 to 691.100 MHz

[Block 27](#) 691.200 to 716.700 MHz

[Block 28](#) 716.800 to 742.300 MHz

[Block 29](#) 742.400 to 767.900 MHz

[Block 30](#) 768.000 to 793.500 MHz

[Block 31](#) 793.600 to 819.100 MHz

[Block 32](#) 819.200 to 844.700 MHz

[Block 33](#) 844.800 to 870.300 MHz

[Television Channel Frequencies](#)

**SPECIALIZING IN:**

# SONY®

CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

# LECTROSONICS®

ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

# sachtler®

TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J

## ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System

# Block 20

Block 20: 512.000 to 537.500 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	512.000	512.100	512.200	512.300	512.400	512.500	512.600	512.700	512.800	512.900	513.000	513.100	513.200	513.300	513.400	513.500
	1	513.600	513.700	513.800	513.900	514.000	514.100	514.200	514.300	514.400	514.500	514.600	514.700	514.800	514.900	515.000	515.100
	2	515.200	515.300	515.400	515.500	515.600	515.700	515.800	515.900	516.000	516.100	516.200	516.300	516.400	516.500	516.600	516.700
	3	516.800	516.900	517.000	517.100	517.200	517.300	517.400	517.500	517.600	517.700	517.800	517.900	518.000	518.100	518.200	518.300
	4	518.400	518.500	518.600	518.700	518.800	518.900	519.000	519.100	519.200	519.300	519.400	519.500	519.600	519.700	519.800	519.900
1.6m	5	520.000	520.100	520.200	520.300	520.400	520.500	520.600	520.700	520.800	520.900	521.000	521.100	521.200	521.300	521.400	521.500
Switch	6	521.600	521.700	521.800	521.900	522.000	522.100	522.200	522.300	522.400	522.500	522.600	522.700	522.800	522.900	523.000	523.100
(Left)	7	523.200	523.300	523.400	523.500	523.600	523.700	523.800	523.900	524.000	524.100	524.200	524.300	524.400	524.500	524.600	524.700
	8	524.800	524.900	525.000	525.100	525.200	525.300	525.400	525.500	525.600	525.700	525.800	525.900	526.000	526.100	526.200	526.300
	9	526.400	526.500	526.600	526.700	526.800	526.900	527.000	527.100	527.200	527.300	527.400	527.500	527.600	527.700	527.800	527.900
	A	528.000	528.100	528.200	528.300	528.400	528.500	528.600	528.700	528.800	528.900	529.000	529.100	529.200	529.300	529.400	529.500
	B	529.600	529.700	529.800	529.900	530.000	530.100	530.200	530.300	530.400	530.500	530.600	530.700	530.800	530.900	531.000	531.100
	C	531.200	531.300	531.400	531.500	531.600	531.700	531.800	531.900	532.000	532.100	532.200	532.300	532.400	532.500	532.600	532.700
	D	532.800	532.900	533.000	533.100	533.200	533.300	533.400	533.500	533.600	533.700	533.800	533.900	534.000	534.100	534.200	534.300
	E	534.400	534.500	534.600	534.700	534.800	534.900	535.000	535.100	535.200	535.300	535.400	535.500	535.600	535.700	535.800	535.900
	F	536.000	536.100	536.200	536.300	536.400	536.500	536.600	536.700	536.800	536.900	537.000	537.100	537.200	537.300	537.400	537.500

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 21

Block 21: 537.600 to 563.100 MHz

100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	537.600	537.700	537.800	537.900	538.000	538.100	538.200	538.300	538.400	538.500	538.600	538.700	538.800	538.900	539.000	539.100
	1	539.200	539.300	539.400	539.500	539.600	539.700	539.800	539.900	540.000	540.100	540.200	540.300	540.400	540.500	540.600	540.700
	2	540.800	540.900	541.000	541.100	541.200	541.300	541.400	541.500	541.600	541.700	541.800	541.900	542.000	542.100	542.200	542.300
	3	542.400	542.500	542.600	542.700	542.800	542.900	543.000	543.100	543.200	543.300	543.400	543.500	543.600	543.700	543.800	543.900
	4	544.000	544.100	544.200	544.300	544.400	544.500	544.600	544.700	544.800	544.900	545.000	545.100	545.200	545.300	545.400	545.500
1.6m	5	545.600	545.700	545.800	545.900	546.000	546.100	546.200	546.300	546.400	546.500	546.600	546.700	546.800	546.900	547.000	547.100
Switch	6	547.200	547.300	547.400	547.500	547.600	547.700	547.800	547.900	548.000	548.100	548.200	548.300	548.400	548.500	548.600	548.700
(Left)	7	548.800	548.900	549.000	549.100	549.200	549.300	549.400	549.500	549.600	549.700	549.800	549.900	550.000	550.100	550.200	550.300
	8	550.400	550.500	550.600	550.700	550.800	550.900	551.000	551.100	551.200	551.300	551.400	551.500	551.600	551.700	551.800	551.900
	9	552.000	552.100	552.200	552.300	552.400	552.500	552.600	552.700	552.800	552.900	553.000	553.100	553.200	553.300	553.400	553.500
	A	553.600	553.700	553.800	553.900	554.000	554.100	554.200	554.300	554.400	554.500	554.600	554.700	554.800	554.900	555.000	555.100
	B	555.200	555.300	555.400	555.500	555.600	555.700	555.800	555.900	556.000	556.100	556.200	556.300	556.400	556.500	556.600	556.700
	C	556.800	556.900	557.000	557.100	557.200	557.300	557.400	557.500	557.600	557.700	557.800	557.900	558.000	558.100	558.200	558.300
	D	558.400	558.500	558.600	558.700	558.800	558.900	559.000	559.100	559.200	559.300	559.400	559.500	559.600	559.700	559.800	559.900
	E	560.000	560.100	560.200	560.300	560.400	560.500	560.600	560.700	560.800	560.900	561.000	561.100	561.200	561.300	561.400	561.500
	F	561.600	561.700	561.800	561.900	562.000	562.100	562.200	562.300	562.400	562.500	562.600	562.700	562.800	562.900	563.000	563.100

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS®**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler®**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 22

Block 22: 563.200 to 588.700 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	563.200	563.300	563.400	563.500	563.600	563.700	563.800	563.900	564.000	564.100	564.200	564.300	564.400	564.500	564.600	564.700
	1	564.800	564.900	565.000	565.100	565.200	565.300	565.400	565.500	565.600	565.700	565.800	565.900	566.000	566.100	566.200	566.300
	2	566.400	566.500	566.600	566.700	566.800	566.900	567.000	567.100	567.200	567.300	567.400	567.500	567.600	567.700	567.800	567.900
	3	568.000	568.100	568.200	568.300	568.400	568.500	568.600	568.700	568.800	568.900	569.000	569.100	569.200	569.300	569.400	569.500
	4	569.600	569.700	569.800	569.900	570.000	570.100	570.200	570.300	570.400	570.500	570.600	570.700	570.800	570.900	571.000	571.100
1.6m	5	571.200	571.300	571.400	571.500	571.600	571.700	571.800	571.900	572.000	572.100	572.200	572.300	572.400	572.500	572.600	572.700
Switch	6	572.800	572.900	573.000	573.100	573.200	573.300	573.400	573.500	573.600	573.700	573.800	573.900	574.000	574.100	574.200	574.300
(Left)	7	574.400	574.500	574.600	574.700	574.800	574.900	575.000	575.100	575.200	575.300	575.400	575.500	575.600	575.700	575.800	575.900
	8	576.000	576.100	576.200	576.300	576.400	576.500	576.600	576.700	576.800	576.900	577.000	577.100	577.200	577.300	577.400	577.500
	9	577.600	577.700	577.800	577.900	578.000	578.100	578.200	578.300	578.400	578.500	578.600	578.700	578.800	578.900	579.000	579.100
	A	579.200	579.300	579.400	579.500	579.600	579.700	579.800	579.900	580.000	580.100	580.200	580.300	580.400	580.500	580.600	580.700
	B	580.800	580.900	581.000	581.100	581.200	581.300	581.400	581.500	581.600	581.700	581.800	581.900	582.000	582.100	582.200	582.300
	C	582.400	582.500	582.600	582.700	582.800	582.900	583.000	583.100	583.200	583.300	583.400	583.500	583.600	583.700	583.800	583.900
	D	584.000	584.100	584.200	584.300	584.400	584.500	584.600	584.700	584.800	584.900	585.000	585.100	585.200	585.300	585.400	585.500
	E	585.600	585.700	585.800	585.900	586.000	586.100	586.200	586.300	586.400	586.500	586.600	586.700	586.800	586.900	587.000	587.100
	F	587.200	587.300	587.400	587.500	587.600	587.700	587.800	587.900	588.000	588.100	588.200	588.300	588.400	588.500	588.600	588.700

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS®**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler®**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 23

Block 23: 588.800 to 614.300 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	588.800	588.900	589.000	589.100	589.200	589.300	589.400	589.500	589.600	589.700	589.800	589.900	590.000	590.100	590.200	590.300
	1	590.400	590.500	590.600	590.700	590.800	590.900	591.000	591.100	591.200	591.300	591.400	591.500	591.600	591.700	591.800	591.900
	2	592.000	592.100	592.200	592.300	592.400	592.500	592.600	592.700	592.800	592.900	593.000	593.100	593.200	593.300	593.400	593.500
	3	593.600	593.700	593.800	593.900	594.000	594.100	594.200	594.300	594.400	594.500	594.600	594.700	594.800	594.900	595.000	595.100
	4	595.200	595.300	595.400	595.500	595.600	595.700	595.800	595.900	596.000	596.100	596.200	596.300	596.400	596.500	596.600	596.700
1.6m	5	596.800	596.900	597.000	597.100	597.200	597.300	597.400	597.500	597.600	597.700	597.800	597.900	598.000	598.100	598.200	598.300
Switch	6	598.400	598.500	598.600	598.700	598.800	598.900	599.000	599.100	599.200	599.300	599.400	599.500	599.600	599.700	599.800	599.900
(Left)	7	600.000	600.100	600.200	600.300	600.400	600.500	600.600	600.700	600.800	600.900	601.000	601.100	601.200	601.300	601.400	601.500
	8	601.600	601.700	601.800	601.900	602.000	602.100	602.200	602.300	602.400	602.500	602.600	602.700	602.800	602.900	603.000	603.100
	9	603.200	603.300	603.400	603.500	603.600	603.700	603.800	603.900	604.000	604.100	604.200	604.300	604.400	604.500	604.600	604.700
	A	604.800	604.900	605.000	605.100	605.200	605.300	605.400	605.500	605.600	605.700	605.800	605.900	606.000	606.100	606.200	606.300
	B	606.400	606.500	606.600	606.700	606.800	606.900	607.000	607.100	607.200	607.300	607.400	607.500	607.600	607.700	607.800	607.900
	C	608.000	608.100	608.200	608.300	608.400	608.500	608.600	608.700	608.800	608.900	609.000	609.100	609.200	609.300	609.400	609.500
	D	609.600	609.700	609.800	609.900	610.000	610.100	610.200	610.300	610.400	610.500	610.600	610.700	610.800	610.900	611.000	611.100
	E	611.200	611.300	611.400	611.500	611.600	611.700	611.800	611.900	612.000	612.100	612.200	612.300	612.400	612.500	612.600	612.700
	F	612.800	612.900	613.000	613.100	613.200	613.300	613.400	613.500	613.600	613.700	613.800	613.900	614.000	614.100	614.200	614.300

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 24

Block 24: 614.400 to 639.900 MHz

100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	614.400	614.500	614.600	614.700	614.800	614.900	615.000	615.100	615.200	615.300	615.400	615.500	615.600	615.700	615.800	615.900
	1	616.000	616.100	616.200	616.300	616.400	616.500	616.600	616.700	616.800	616.900	617.000	617.100	617.200	617.300	617.400	617.500
	2	617.600	617.700	617.800	617.900	618.000	618.100	618.200	618.300	618.400	618.500	618.600	618.700	618.800	618.900	619.000	619.100
	3	619.200	619.300	619.400	619.500	619.600	619.700	619.800	619.900	620.000	620.100	620.200	620.300	620.400	620.500	620.600	620.700
	4	620.800	620.900	621.000	621.100	621.200	621.300	621.400	621.500	621.600	621.700	621.800	621.900	622.000	622.100	622.200	622.300
1.6m	5	622.400	622.500	622.600	622.700	622.800	622.900	623.000	623.100	623.200	623.300	623.400	623.500	623.600	623.700	623.800	623.900
Switch	6	624.000	624.100	624.200	624.300	624.400	624.500	624.600	624.700	624.800	624.900	625.000	625.100	625.200	625.300	625.400	625.500
(Left)	7	625.600	625.700	625.800	625.900	626.000	626.100	626.200	626.300	626.400	626.500	626.600	626.700	626.800	626.900	627.000	627.100
	8	627.200	627.300	627.400	627.500	627.600	627.700	627.800	627.900	628.000	628.100	628.200	628.300	628.400	628.500	628.600	628.700
	9	628.800	628.900	629.000	629.100	629.200	629.300	629.400	629.500	629.600	629.700	629.800	629.900	630.000	630.100	630.200	630.300
	A	630.400	630.500	630.600	630.700	630.800	630.900	631.000	631.100	631.200	631.300	631.400	631.500	631.600	631.700	631.800	631.900
	B	632.000	632.100	632.200	632.300	632.400	632.500	632.600	632.700	632.800	632.900	633.000	633.100	633.200	633.300	633.400	633.500
	C	633.600	633.700	633.800	633.900	634.000	634.100	634.200	634.300	634.400	634.500	634.600	634.700	634.800	634.900	635.000	635.100
	D	635.200	635.300	635.400	635.500	635.600	635.700	635.800	635.900	636.000	636.100	636.200	636.300	636.400	636.500	636.600	636.700
	E	636.800	636.900	637.000	637.100	637.200	637.300	637.400	637.500	637.600	637.700	637.800	637.900	638.000	638.100	638.200	638.300
	F	638.400	638.500	638.600	638.700	638.800	638.900	639.000	639.100	639.200	639.300	639.400	639.500	639.600	639.700	639.800	639.900

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J

## ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System

# Block 25

Block 25: 640.000 to 665.500 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	640.000	640.100	640.200	640.300	640.400	640.500	640.600	640.700	640.800	640.900	641.000	641.100	641.200	641.300	641.400	641.500
	1	641.600	641.700	641.800	641.900	642.000	642.100	642.200	642.300	642.400	642.500	642.600	642.700	642.800	642.900	643.000	643.100
	2	643.200	643.300	643.400	643.500	643.600	643.700	643.800	643.900	644.000	644.100	644.200	644.300	644.400	644.500	644.600	644.700
	3	644.800	644.900	645.000	645.100	645.200	645.300	645.400	645.500	645.600	645.700	645.800	645.900	646.000	646.100	646.200	646.300
	4	646.400	646.500	646.600	646.700	646.800	646.900	647.000	647.100	647.200	647.300	647.400	647.500	647.600	647.700	647.800	647.900
1.6m	5	648.000	648.100	648.200	648.300	648.400	648.500	648.600	648.700	648.800	648.900	649.000	649.100	649.200	649.300	649.400	649.500
Switch	6	649.600	649.700	649.800	649.900	650.000	650.100	650.200	650.300	650.400	650.500	650.600	650.700	650.800	650.900	651.000	651.100
(Left)	7	651.200	651.300	651.400	651.500	651.600	651.700	651.800	651.900	652.000	652.100	652.200	652.300	652.400	652.500	652.600	652.700
	8	652.800	652.900	653.000	653.100	653.200	653.300	653.400	653.500	653.600	653.700	653.800	653.900	654.000	654.100	654.200	654.300
	9	654.400	654.500	654.600	654.700	654.800	654.900	655.000	655.100	655.200	655.300	655.400	655.500	655.600	655.700	655.800	655.900
	A	656.000	656.100	656.200	656.300	656.400	656.500	656.600	656.700	656.800	656.900	657.000	657.100	657.200	657.300	657.400	657.500
	B	657.600	657.700	657.800	657.900	658.000	658.100	658.200	658.300	658.400	658.500	658.600	658.700	658.800	658.900	659.000	659.100
	C	659.200	659.300	659.400	659.500	659.600	659.700	659.800	659.900	660.000	660.100	660.200	660.300	660.400	660.500	660.600	660.700
	D	660.800	660.900	661.000	661.100	661.200	661.300	661.400	661.500	661.600	661.700	661.800	661.900	662.000	662.100	662.200	662.300
	E	662.400	662.500	662.600	662.700	662.800	662.900	663.000	663.100	663.200	663.300	663.400	663.500	663.600	663.700	663.800	663.900
	F	664.000	664.100	664.200	664.300	664.400	664.500	664.600	664.700	664.800	664.900	665.000	665.100	665.200	665.300	665.400	665.500

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 26

Block 26: 665.600 to 691.100 MHz

100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	665.600	665.700	665.800	665.900	666.000	666.100	666.200	666.300	666.400	666.500	666.600	666.700	666.800	666.900	667.000	667.100
	1	667.200	667.300	667.400	667.500	667.600	667.700	667.800	667.900	668.000	668.100	668.200	668.300	668.400	668.500	668.600	668.700
	2	668.800	668.900	669.000	669.100	669.200	669.300	669.400	669.500	669.600	669.700	669.800	669.900	670.000	670.100	670.200	670.300
	3	670.400	670.500	670.600	670.700	670.800	670.900	671.000	671.100	671.200	671.300	671.400	671.500	671.600	671.700	671.800	671.900
	4	672.000	672.100	672.200	672.300	672.400	672.500	672.600	672.700	672.800	672.900	673.000	673.100	673.200	673.300	673.400	673.500
1.6m	5	673.600	673.700	673.800	673.900	674.000	674.100	674.200	674.300	674.400	674.500	674.600	674.700	674.800	674.900	675.000	675.100
Switch	6	675.200	675.300	675.400	675.500	675.600	675.700	675.800	675.900	676.000	676.100	676.200	676.300	676.400	676.500	676.600	676.700
(Left)	7	676.800	676.900	677.000	677.100	677.200	677.300	677.400	677.500	677.600	677.700	677.800	677.900	678.000	678.100	678.200	678.300
	8	678.400	678.500	678.600	678.700	678.800	678.900	679.000	679.100	679.200	679.300	679.400	679.500	679.600	679.700	679.800	679.900
	9	680.000	680.100	680.200	680.300	680.400	680.500	680.600	680.700	680.800	680.900	681.000	681.100	681.200	681.300	681.400	681.500
	A	681.600	681.700	681.800	681.900	682.000	682.100	682.200	682.300	682.400	682.500	682.600	682.700	682.800	682.900	683.000	683.100
	B	683.200	683.300	683.400	683.500	683.600	683.700	683.800	683.900	684.000	684.100	684.200	684.300	684.400	684.500	684.600	684.700
	C	684.800	684.900	685.000	685.100	685.200	685.300	685.400	685.500	685.600	685.700	685.800	685.900	686.000	686.100	686.200	686.300
	D	686.400	686.500	686.600	686.700	686.800	686.900	687.000	687.100	687.200	687.300	687.400	687.500	687.600	687.700	687.800	687.900
	E	688.000	688.100	688.200	688.300	688.400	688.500	688.600	688.700	688.800	688.900	689.000	689.100	689.200	689.300	689.400	689.500
	F	689.600	689.700	689.800	689.900	690.000	690.100	690.200	690.300	690.400	690.500	690.600	690.700	690.800	690.900	691.000	691.100

**SPECIALIZING IN:**

**SONY**

CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**

ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**

TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS



# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 27

Block 27: 691.200 to 716.700 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	691.200	691.300	691.400	691.500	691.600	691.700	691.800	691.900	692.000	692.100	692.200	692.300	692.400	692.500	692.600	692.700
	1	692.800	692.900	693.000	693.100	693.200	693.300	693.400	693.500	693.600	693.700	693.800	693.900	694.000	694.100	694.200	694.300
	2	694.400	694.500	694.600	694.700	694.800	694.900	695.000	695.100	695.200	695.300	695.400	695.500	695.600	695.700	695.800	695.900
	3	696.000	696.100	696.200	696.300	696.400	696.500	696.600	696.700	696.800	696.900	697.000	697.100	697.200	697.300	697.400	697.500
	4	697.600	697.700	697.800	697.900	698.000	698.100	698.200	698.300	698.400	698.500	698.600	698.700	698.800	698.900	699.000	699.100
1.6m	5	699.200	699.300	699.400	699.500	699.600	699.700	699.800	699.900	700.000	700.100	700.200	700.300	700.400	700.500	700.600	700.700
Switch	6	700.800	700.900	701.000	701.100	701.200	701.300	701.400	701.500	701.600	701.700	701.800	701.900	702.000	702.100	702.200	702.300
(Left)	7	702.400	702.500	702.600	702.700	702.800	702.900	703.000	703.100	703.200	703.300	703.400	703.500	703.600	703.700	703.800	703.900
	8	704.000	704.100	704.200	704.300	704.400	704.500	704.600	704.700	704.800	704.900	705.000	705.100	705.200	705.300	705.400	705.500
	9	705.600	705.700	705.800	705.900	706.000	706.100	706.200	706.300	706.400	706.500	706.600	706.700	706.800	706.900	707.000	707.100
	A	707.200	707.300	707.400	707.500	707.600	707.700	707.800	707.900	708.000	708.100	708.200	708.300	708.400	708.500	708.600	708.700
	B	708.800	708.900	709.000	709.100	709.200	709.300	709.400	709.500	709.600	709.700	709.800	709.900	710.000	710.100	710.200	710.300
	C	710.400	710.500	710.600	710.700	710.800	710.900	711.000	711.100	711.200	711.300	711.400	711.500	711.600	711.700	711.800	711.900
	D	712.000	712.100	712.200	712.300	712.400	712.500	712.600	712.700	712.800	712.900	713.000	713.100	713.200	713.300	713.400	713.500
	E	713.600	713.700	713.800	713.900	714.000	714.100	714.200	714.300	714.400	714.500	714.600	714.700	714.800	714.900	715.000	715.100
	F	715.200	715.300	715.400	715.500	715.600	715.700	715.800	715.900	716.000	716.100	716.200	716.300	716.400	716.500	716.600	716.700

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 28

Block 28: 716.800 to 742.300 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	716.800	716.900	717.000	717.100	717.200	717.300	717.400	717.500	717.600	717.700	717.800	717.900	718.000	718.100	718.200	718.300
	1	718.400	718.500	718.600	718.700	718.800	718.900	719.000	719.100	719.200	719.300	719.400	719.500	719.600	719.700	719.800	719.900
	2	720.000	720.100	720.200	720.300	720.400	720.500	720.600	720.700	720.800	720.900	721.000	721.100	721.200	721.300	721.400	721.500
	3	721.600	721.700	721.800	721.900	722.000	722.100	722.200	722.300	722.400	722.500	722.600	722.700	722.800	722.900	723.000	723.100
	4	723.200	723.300	723.400	723.500	723.600	723.700	723.800	723.900	724.000	724.100	724.200	724.300	724.400	724.500	724.600	724.700
1.6m	5	724.800	724.900	725.000	725.100	725.200	725.300	725.400	725.500	725.600	725.700	725.800	725.900	726.000	726.100	726.200	726.300
Switch	6	726.400	726.500	726.600	726.700	726.800	726.900	727.000	727.100	727.200	727.300	727.400	727.500	727.600	727.700	727.800	727.900
(Left)	7	728.000	728.100	728.200	728.300	728.400	728.500	728.600	728.700	728.800	728.900	729.000	729.100	729.200	729.300	729.400	729.500
	8	729.600	729.700	729.800	729.900	730.000	730.100	730.200	730.300	730.400	730.500	730.600	730.700	730.800	730.900	731.000	731.100
	9	731.200	731.300	731.400	731.500	731.600	731.700	731.800	731.900	732.000	732.100	732.200	732.300	732.400	732.500	732.600	732.700
	A	732.800	732.900	733.000	733.100	733.200	733.300	733.400	733.500	733.600	733.700	733.800	733.900	734.000	734.100	734.200	734.300
	B	734.400	734.500	734.600	734.700	734.800	734.900	735.000	735.100	735.200	735.300	735.400	735.500	735.600	735.700	735.800	735.900
	C	736.000	736.100	736.200	736.300	736.400	736.500	736.600	736.700	736.800	736.900	737.000	737.100	737.200	737.300	737.400	737.500
	D	737.600	737.700	737.800	737.900	738.000	738.100	738.200	738.300	738.400	738.500	738.600	738.700	738.800	738.900	739.000	739.100
	E	739.200	739.300	739.400	739.500	739.600	739.700	739.800	739.900	740.000	740.100	740.200	740.300	740.400	740.500	740.600	740.700
	F	740.800	740.900	741.000	741.100	741.200	741.300	741.400	741.500	741.600	741.700	741.800	741.900	742.000	742.100	742.200	742.300

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 29

Block 29: 742.400 to 767.900 MHz

100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	742.400	742.500	742.600	742.700	742.800	742.900	743.000	743.100	743.200	743.300	743.400	743.500	743.600	743.700	743.800	743.900
	1	744.000	744.100	744.200	744.300	744.400	744.500	744.600	744.700	744.800	744.900	745.000	745.100	745.200	745.300	745.400	745.500
	2	745.600	745.700	745.800	745.900	746.000	746.100	746.200	746.300	746.400	746.500	746.600	746.700	746.800	746.900	747.000	747.100
	3	747.200	747.300	747.400	747.500	747.600	747.700	747.800	747.900	748.000	748.100	748.200	748.300	748.400	748.500	748.600	748.700
	4	748.800	748.900	749.000	749.100	749.200	749.300	749.400	749.500	749.600	749.700	749.800	749.900	750.000	750.100	750.200	750.300
1.6m	5	750.400	750.500	750.600	750.700	750.800	750.900	751.000	751.100	751.200	751.300	751.400	751.500	751.600	751.700	751.800	751.900
Switch	6	752.000	752.100	752.200	752.300	752.400	752.500	752.600	752.700	752.800	752.900	753.000	753.100	753.200	753.300	753.400	753.500
(Left)	7	753.600	753.700	753.800	753.900	754.000	754.100	754.200	754.300	754.400	754.500	754.600	754.700	754.800	754.900	755.000	755.100
	8	755.200	755.300	755.400	755.500	755.600	755.700	755.800	755.900	756.000	756.100	756.200	756.300	756.400	756.500	756.600	756.700
	9	756.800	756.900	757.000	757.100	757.200	757.300	757.400	757.500	757.600	757.700	757.800	757.900	758.000	758.100	758.200	758.300
	A	758.400	758.500	758.600	758.700	758.800	758.900	759.000	759.100	759.200	759.300	759.400	759.500	759.600	759.700	759.800	759.900
	B	760.000	760.100	760.200	760.300	760.400	760.500	760.600	760.700	760.800	760.900	761.000	761.100	761.200	761.300	761.400	761.500
	C	761.600	761.700	761.800	761.900	762.000	762.100	762.200	762.300	762.400	762.500	762.600	762.700	762.800	762.900	763.000	763.100
	D	763.200	763.300	763.400	763.500	763.600	763.700	763.800	763.900	764.000	764.100	764.200	764.300	764.400	764.500	764.600	764.700
	E	764.800	764.900	765.000	765.100	765.200	765.300	765.400	765.500	765.600	765.700	765.800	765.900	766.000	766.100	766.200	766.300
	F	766.400	766.500	766.600	766.700	766.800	766.900	767.000	767.100	767.200	767.300	767.400	767.500	767.600	767.700	767.800	767.900

**SPECIALIZING IN:**

**SONY**

CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS®**

ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler®**

TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 30

Block 30: 768.000 to 793.500 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	768.000	768.100	768.200	768.300	768.400	768.500	768.600	768.700	768.800	768.900	769.000	769.100	769.200	769.300	769.400	769.500
	1	769.600	769.700	769.800	769.900	770.000	770.100	770.200	770.300	770.400	770.500	770.600	770.700	770.800	770.900	771.000	771.100
	2	771.200	771.300	771.400	771.500	771.600	771.700	771.800	771.900	772.000	772.100	772.200	772.300	772.400	772.500	772.600	772.700
	3	772.800	772.900	773.000	773.100	773.200	773.300	773.400	773.500	773.600	773.700	773.800	773.900	774.000	774.100	774.200	774.300
	4	774.400	774.500	774.600	774.700	774.800	774.900	775.000	775.100	775.200	775.300	775.400	775.500	775.600	775.700	775.800	775.900
1.6m	5	776.000	776.100	776.200	776.300	776.400	776.500	776.600	776.700	776.800	776.900	777.000	777.100	777.200	777.300	777.400	777.500
Switch	6	777.600	777.700	777.800	777.900	778.000	778.100	778.200	778.300	778.400	778.500	778.600	778.700	778.800	778.900	779.000	779.100
(Left)	7	779.200	779.300	779.400	779.500	779.600	779.700	779.800	779.900	780.000	780.100	780.200	780.300	780.400	780.500	780.600	780.700
	8	780.800	780.900	781.000	781.100	781.200	781.300	781.400	781.500	781.600	781.700	781.800	781.900	782.000	782.100	782.200	782.300
	9	782.400	782.500	782.600	782.700	782.800	782.900	783.000	783.100	783.200	783.300	783.400	783.500	783.600	783.700	783.800	783.900
	A	784.000	784.100	784.200	784.300	784.400	784.500	784.600	784.700	784.800	784.900	785.000	785.100	785.200	785.300	785.400	785.500
	B	785.600	785.700	785.800	785.900	786.000	786.100	786.200	786.300	786.400	786.500	786.600	786.700	786.800	786.900	787.000	787.100
	C	787.200	787.300	787.400	787.500	787.600	787.700	787.800	787.900	788.000	788.100	788.200	788.300	788.400	788.500	788.600	788.700
	D	788.800	788.900	789.000	789.100	789.200	789.300	789.400	789.500	789.600	789.700	789.800	789.900	790.000	790.100	790.200	790.300
	E	790.400	790.500	790.600	790.700	790.800	790.900	791.000	791.100	791.200	791.300	791.400	791.500	791.600	791.700	791.800	791.900
	F	792.000	792.100	792.200	792.300	792.400	792.500	792.600	792.700	792.800	792.900	793.000	793.100	793.200	793.300	793.400	793.500

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS®**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler®**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 31

Block 31: 793.600 to 819.100 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	793.600	793.700	793.800	793.900	794.000	794.100	794.200	794.300	794.400	794.500	794.600	794.700	794.800	794.900	795.000	795.100
	1	795.200	795.300	795.400	795.500	795.600	795.700	795.800	795.900	796.000	796.100	796.200	796.300	796.400	796.500	796.600	796.700
	2	796.800	796.900	797.000	797.100	797.200	797.300	797.400	797.500	797.600	797.700	797.800	797.900	798.000	798.100	798.200	798.300
	3	798.400	798.500	798.600	798.700	798.800	798.900	799.000	799.100	799.200	799.300	799.400	799.500	799.600	799.700	799.800	799.900
	4	800.000	800.100	800.200	800.300	800.400	800.500	800.600	800.700	800.800	800.900	801.000	801.100	801.200	801.300	801.400	801.500
1.6m	5	801.600	801.700	801.800	801.900	802.000	802.100	802.200	802.300	802.400	802.500	802.600	802.700	802.800	802.900	803.000	803.100
Switch	6	803.200	803.300	803.400	803.500	803.600	803.700	803.800	803.900	804.000	804.100	804.200	804.300	804.400	804.500	804.600	804.700
(Left)	7	804.800	804.900	805.000	805.100	805.200	805.300	805.400	805.500	805.600	805.700	805.800	805.900	806.000	806.100	806.200	806.300
	8	806.400	806.500	806.600	806.700	806.800	806.900	807.000	807.100	807.200	807.300	807.400	807.500	807.600	807.700	807.800	807.900
	9	808.000	808.100	808.200	808.300	808.400	808.500	808.600	808.700	808.800	808.900	809.000	809.100	809.200	809.300	809.400	809.500
	A	809.600	809.700	809.800	809.900	810.000	810.100	810.200	810.300	810.400	810.500	810.600	810.700	810.800	810.900	811.000	811.100
	B	811.200	811.300	811.400	811.500	811.600	811.700	811.800	811.900	812.000	812.100	812.200	812.300	812.400	812.500	812.600	812.700
	C	812.800	812.900	813.000	813.100	813.200	813.300	813.400	813.500	813.600	813.700	813.800	813.900	814.000	814.100	814.200	814.300
	D	814.400	814.500	814.600	814.700	814.800	814.900	815.000	815.100	815.200	815.300	815.400	815.500	815.600	815.700	815.800	815.900
	E	816.000	816.100	816.200	816.300	816.400	816.500	816.600	816.700	816.800	816.900	817.000	817.100	817.200	817.300	817.400	817.500
	F	817.600	817.700	817.800	817.900	818.000	818.100	818.200	818.300	818.400	818.500	818.600	818.700	818.800	818.900	819.000	819.100

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 32

Block 32: 819.200 to 844.700 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	819.200	819.300	819.400	819.500	819.600	819.700	819.800	819.900	820.000	820.100	820.200	820.300	820.400	820.500	820.600	820.700
	1	820.800	820.900	821.000	821.100	821.200	821.300	821.400	821.500	821.600	821.700	821.800	821.900	822.000	822.100	822.200	822.300
	2	822.400	822.500	822.600	822.700	822.800	822.900	823.000	823.100	823.200	823.300	823.400	823.500	823.600	823.700	823.800	823.900
	3	824.000	824.100	824.200	824.300	824.400	824.500	824.600	824.700	824.800	824.900	825.000	825.100	825.200	825.300	825.400	825.500
	4	825.600	825.700	825.800	825.900	826.000	826.100	826.200	826.300	826.400	826.500	826.600	826.700	826.800	826.900	827.000	827.100
1.6m	5	827.200	827.300	827.400	827.500	827.600	827.700	827.800	827.900	828.000	828.100	828.200	828.300	828.400	828.500	828.600	828.700
Switch	6	828.800	828.900	829.000	829.100	829.200	829.300	829.400	829.500	829.600	829.700	829.800	829.900	830.000	830.100	830.200	830.300
(Left)	7	830.400	830.500	830.600	830.700	830.800	830.900	831.000	831.100	831.200	831.300	831.400	831.500	831.600	831.700	831.800	831.900
	8	832.000	832.100	832.200	832.300	832.400	832.500	832.600	832.700	832.800	832.900	833.000	833.100	833.200	833.300	833.400	833.500
	9	833.600	833.700	833.800	833.900	834.000	834.100	834.200	834.300	834.400	834.500	834.600	834.700	834.800	834.900	835.000	835.100
	A	835.200	835.300	835.400	835.500	835.600	835.700	835.800	835.900	836.000	836.100	836.200	836.300	836.400	836.500	836.600	836.700
	B	836.800	836.900	837.000	837.100	837.200	837.300	837.400	837.500	837.600	837.700	837.800	837.900	838.000	838.100	838.200	838.300
	C	838.400	838.500	838.600	838.700	838.800	838.900	839.000	839.100	839.200	839.300	839.400	839.500	839.600	839.700	839.800	839.900
	D	840.000	840.100	840.200	840.300	840.400	840.500	840.600	840.700	840.800	840.900	841.000	841.100	841.200	841.300	841.400	841.500
	E	841.600	841.700	841.800	841.900	842.000	842.100	842.200	842.300	842.400	842.500	842.600	842.700	842.800	842.900	843.000	843.100
	F	843.200	843.300	843.400	843.500	843.600	843.700	843.800	843.900	844.000	844.100	844.200	844.300	844.400	844.500	844.600	844.700

**SPECIALIZING IN:**

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS®**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler®**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

www.TheBroadcastShop.com  
service@TheBroadcastShop.com

## Lectrosonics Wireless System Block 33

Block 33: 844.800 to 870.300 MHz																	
100K Switch (Right)																	
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F	
	0	844.800	844.900	845.000	845.100	845.200	845.300	845.400	845.500	845.600	845.700	845.800	845.900	846.000	846.100	846.200	846.300
	1	846.400	846.500	846.600	846.700	846.800	846.900	847.000	847.100	847.200	847.300	847.400	847.500	847.600	847.700	847.800	847.900
	2	848.000	848.100	848.200	848.300	848.400	848.500	848.600	848.700	848.800	848.900	849.000	849.100	849.200	849.300	849.400	849.500
	3	849.600	849.700	849.800	849.900	850.000	850.100	850.200	850.300	850.400	850.500	850.600	850.700	850.800	850.900	851.000	851.100
	4	851.200	851.300	851.400	851.500	851.600	851.700	851.800	851.900	852.000	852.100	852.200	852.300	852.400	852.500	852.600	852.700
1.6m	5	852.800	852.900	853.000	853.100	853.200	853.300	853.400	853.500	853.600	853.700	853.800	853.900	854.000	854.100	854.200	854.300
Switch	6	854.400	854.500	854.600	854.700	854.800	854.900	855.000	855.100	855.200	855.300	855.400	855.500	855.600	855.700	855.800	855.900
(Left)	7	856.000	856.100	856.200	856.300	856.400	856.500	856.600	856.700	856.800	856.900	857.000	857.100	857.200	857.300	857.400	857.500
	8	857.600	857.700	857.800	857.900	858.000	858.100	858.200	858.300	858.400	858.500	858.600	858.700	858.800	858.900	859.000	859.100
	9	859.200	859.300	859.400	859.500	859.600	859.700	859.800	859.900	860.000	860.100	860.200	860.300	860.400	860.500	860.600	860.700
	A	860.800	860.900	861.000	861.100	861.200	861.300	861.400	861.500	861.600	861.700	861.800	861.900	862.000	862.100	862.200	862.300
	B	862.400	862.500	862.600	862.700	862.800	862.900	863.000	863.100	863.200	863.300	863.400	863.500	863.600	863.700	863.800	863.900
	C	864.000	864.100	864.200	864.300	864.400	864.500	864.600	864.700	864.800	864.900	865.000	865.100	865.200	865.300	865.400	865.500
	D	865.600	865.700	865.800	865.900	866.000	866.100	866.200	866.300	866.400	866.500	866.600	866.700	866.800	866.900	867.000	867.100
	E	867.200	867.300	867.400	867.500	867.600	867.700	867.800	867.900	868.000	868.100	868.200	868.300	868.400	868.500	868.600	868.700
	F	868.800	868.900	869.000	869.100	869.200	869.300	869.400	869.500	869.600	869.700	869.800	869.900	870.000	870.100	870.200	870.300

### SPECIALIZING IN:

**SONY**  
CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS**  
ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler**  
TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS

# Television Channel Frequencies

TV Channel	Starting Frequency	Ending Frequency
7	174.000 mhz	179.999 mhz
8	180.000 mhz	185.999 mhz
9	186.000 mhz	191.999 mhz
10	192.000 mhz	197.999 mhz
11	198.000 mhz	203.999 mhz
12	204.000 mhz	209.999 mhz
13	210.000 mhz	215.999 mhz
14	470.000 mhz	475.999 mhz
15	476.000 mhz	481.999 mhz
16	482.000 mhz	487.999 mhz
17	488.000 mhz	493.999 mhz
18	494.000 mhz	499.999 mhz
19	500.000 mhz	505.999 mhz
20	506.000 mhz	511.999 mhz
21	512.000 mhz	517.999 mhz
22	518.000 mhz	523.999 mhz
23	524.000 mhz	529.999 mhz
24	530.000 mhz	535.999 mhz
25	536.000 mhz	541.999 mhz
26	542.000 mhz	547.999 mhz
27	548.000 mhz	553.999 mhz
28	554.000 mhz	559.999 mhz
29	560.000 mhz	565.999 mhz
30	566.000 mhz	571.999 mhz
31	572.000 mhz	577.999 mhz
32	578.000 mhz	583.999 mhz
33	584.000 mhz	589.999 mhz
34	590.000 mhz	595.999 mhz
35	596.000 mhz	601.999 mhz
36	602.000 mhz	607.999 mhz
37	608.000 mhz	613.999 mhz
38	614.000 mhz	619.999 mhz
39	620.000 mhz	625.999 mhz
40	626.000 mhz	631.999 mhz
41	632.000 mhz	637.999 mhz
42	638.000 mhz	643.999 mhz
43	644.000 mhz	649.999 mhz
44	650.000 mhz	655.999 mhz
45	656.000 mhz	661.999 mhz
46	662.000 mhz	667.999 mhz
47	668.000 mhz	673.999 mhz
48	674.000 mhz	679.999 mhz
49	680.000 mhz	685.999 mhz
50	686.000 mhz	691.999 mhz
51	692.000 mhz	697.999 mhz
52	698.000 mhz	703.999 mhz
53	704.000 mhz	709.999 mhz
54	710.000 mhz	715.999 mhz
55	716.000 mhz	721.999 mhz
56	722.000 mhz	727.999 mhz
57	728.000 mhz	733.999 mhz
58	734.000 mhz	739.999 mhz
59	740.000 mhz	745.999 mhz
60	746.000 mhz	751.999 mhz
61	752.000 mhz	757.999 mhz
62	758.000 mhz	763.999 mhz
63	764.000 mhz	769.999 mhz
64	770.000 mhz	775.999 mhz
65	776.000 mhz	781.999 mhz
66	782.000 mhz	787.999 mhz
67	788.000 mhz	793.999 mhz
68	794.000 mhz	799.999 mhz
69	800.000 mhz	805.999 mhz

# SA & J ELECTRONICS

SA & J Electronics Inc.  
1020 N. North Branch St.  
Chicago, IL 60622-4209

Phone (312) 867-1400  
Fax (312) 867-1140

[www.TheBroadcastShop.com](http://www.TheBroadcastShop.com)  
[service@TheBroadcastShop.com](mailto:service@TheBroadcastShop.com)

**SPECIALIZING IN:**

**SONY**

CAMERAS • VTR'S • MONITORS  
SERVICE • PARTS

**LECTROSONICS®**

ENG WIRELESS MIC SYSTEMS  
SERVICE • SALES • ACCESSORIES • PARTS

**sachtler®**

TRIPOD HEADS & STICKS  
SERVICE • SALES • ACCESSORIES • PARTS